

# PC15250 MK2

## Phase Sequence Indicator



### Key features

- Bright LED indication of live phases
- Clear and simple display of direction of phase rotation
- Easy identification of faulty lines
- No batteries required
- Retractable probe shrouds to GS38

CAT IV  
600V

The PC15250 quickly and simply proves the presence of all three live phases (or identifies which are faulty) and shows the sequence of phase rotation when all three phases are confirmed as present.

The PC15250 gives a fast, effective, battery-free method of identifying unmarked cables and ensures that 3-phase outlets and machines are wired correctly.

The retractable GS38 fused probe shrouds give a choice between long exposed tips, for reaching difficult to access contacts, and shorter tips for increased safety.

Supplied with L1 and L2 fused probes while L3 is a fused croc clip, the two-handed application is both safe and secure.

Optional colour coded and interchangeable croc clips for probes and probes for croc clips are available.



Keeping You Safe

# PC15250 MK2

## Phase Sequence Indicator

Specifications

FUNCTION	PC15250
<b>ELECTRICAL</b>	
Input voltage range	50V to 600V AC (Phase to Phase)
Input frequency	40 to 60Hz
Input current	< 3mA
<b>ENVIRONMENTAL</b>	
Location	Suitable for indoor use, and outdoor use in dry weather conditions only
Altitude	up to 2000m
Temperature (operating & storage)	-10°C to 55°C
Humidity (operating & Storage)	≤85% R.H
Mains supply voltage fluctuations	±10%
Pollution degree	2
<b>GENERAL</b>	
Power	from circuit under test
Fuses	600V 0.5A 50kA HRC rated fuses (6x32mm) x 3, one in each probe
Dimensions	116(L) x 69(W) x 25(D) mm
Weight packed	320g approx.
<b>SAFETY</b>	
Conforms to	Conforms to GS38 & BS EN61557-7:2007, CAT IV 600V Class II, Double Insulation
<b>EMC</b>	
Conforms to	BS EN 61326-2-2:2021

### Included

L1 and L2 fused probes  
L3 fused croc clip  
Instructions

### Related products

PSI4000 Non Contact Phase Sequence Indicator  
PSI4300 Non Contact Utility Phase Sequence Indicator

Martindale Electric Co. Ltd.  
Metrohm House, 12 Imperial Park,  
Imperial Way, Watford WD24 4PP.  
T: 01923 441717 F: 01923 446900  
[www.martindale-electric.co.uk](http://www.martindale-electric.co.uk)  
[sales@martindale-electric.co.uk](mailto:sales@martindale-electric.co.uk)

### Ver. C1.1

Due to policy of continuous development, Martindale Electric reserves the right to alter equipment specification and description outlined in this document without prior notice. No part of this document shall be deemed to be part of any contract for the equipment unless specifically referred to as an inclusion within such contract. © 2022 Martindale Electric Co. Ltd.